



**BUREAU
VERITAS**

Certificate of compliance

Applicant: Kostal Solar Electric
Hanferstrasse 6
79108 Freiburg
Germany

Product: Battery Inverter

Model: PLENTICORE BI 5.5/26 PLENTICORE BI 10/26

Use in accordance with regulations:

Automatic disconnection device with three-phase mains surveillance in accordance with Engineering Recommendation G99/1 for Battery systems with a three-phase parallel coupling via an inverter in the public mains supply. The automatic disconnection device is an integral part of the aforementioned inverter. This serves as a replacement for the disconnection device with isolating function, which can be accessed the distribution network provider at any time.

Applied rules and standards:

Engineering Recommendation G99/1-6:2020

Requirements for the connection of generation equipment in parallel with public distribution networks

DIN V VDE V 0126-1-1:2006-02 (4.1 Functional safety)

Automatic disconnection device between a generator and the public low-voltage grid

At the time of issue of this certificate the safety concept of an aforementioned representative product corresponds to the valid safety specifications for the specified use in accordance with regulations.

Report number: 19TH0374-BI-G99/1_0

Certification program: NSOP-0032-DEU-ZE-V01

Certificate number: U20-0994

Date of issue: 2020-12-10

Certification body

Thomas Lammell

*Certification body Bureau Veritas Consumer Products Services Germany GmbH accredited according to DIN EN ISO/IEC 17065
A partial representation of the certificate requires the written approval of Bureau Veritas Consumer Products Services Germany GmbH*

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Type Approval and declaration of compliance with the requirements of Engineering Recommendation G99.

PGM Technology:	Battery Inverter		
Manufacturer / applicant:	Kostal Solar Elektrik GmbH		
Address:	Hanferstraße 6, 79108 Freiburg im Breisgau		
Tel	+49 761 47744 - 100	Fax:	+49 761 47744 - 111
Email:	info-solar@kostal.com	Website:	https://www.kostal-solar-electric.com/

Rated values	PLENTICORE BI 5.5/26	PLENTICORE BI 10/26	--	--
In-/Output DC voltage range [V]	120 – 650	120 – 650	--	--
In-/Output Input DC current [A]	26	26	--	--
Output AC voltage [V]	3N~, 400V, 50Hz	3N~, 400V, 50Hz	--	--
Output AC current [A]	7,94	16,04	--	--
Output power [VA]	5500	10000	--	--

Firmware version	Beginning with FW = 01.46 / PAR = 03.19
-------------------------	---

Measurement period:	2019-08-02 - 2019-11-07, 2020-04-06 – 2020-05-29, 2020-11-10 – 2020-11-30
----------------------------	---

Description of the structure of the power generation unit:

The power generation unit is equipped with a DC and line-side EMC filter. The power generation unit has no galvanic isolation between DC input and AC output. Output switch-off is performed with single-fault tolerance based on two series-connected relays in line and neutral. This enables a safe disconnection of the power generation unit from the network in case of error.

Differences between Generating Units:

The inverters are divided into two performance classes, namely classes A and B.

The inverters of class A, PLENTICORE plus 5.5 and PLENTICORE BI 5.5/26 are based on the inverter PLENTICORE plus 5.5. All the models use the same hardware and software. The model PLENTICORE plus 5.5 is equipped with two DC input and with two MPP tracker. The model PLENTICORE BI 5.5/26 is equipped with one DC input (Batterie).

The inverters of class B, PLENTICORE plus 10 and PLENTICORE BI 10/26 are based on the inverter PLENTICORE plus 10. All the models use the same hardware and software. The model PLENTICORE plus 10 and PIKO IQ 10 are equipped with two DC input and with two MPP tracker. The model PLENTICORE BI 10/26 is equipped with one DC input (Batterie).

The Class A and Class B power models have a different inverter-bridge, EMC filter, higher current rating. In addition Class B models have a DC input and MPP tracker. Compared to Type A.

The tests have been performed on the PLENTICORE plus 5.5 and the PLENTICORE plus 10.0 model and are valid for the whole series.

The above stated Generating Units are tested according the requirements in the Engineering Recommendation G99/1. Any modification that affects the stated tests must be named by the manufacturer/supplier of the product to ensure that the product meets all requirements of the Engineering Recommendation G99/1.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Operating Range.	
Test 1	Voltage = 85% of nominal (195,5V) Frequency = 47Hz Power Factor = 1 Period of test 20 s
Connection:	Always connected
Limit:	Always connected
Test 2	Voltage = 85% of nominal (195,5V) Frequency = 47,5Hz Power Factor = 1 Period of test 90 minutes
Connection:	Always connected
Limit:	Always connected
Test 3	Voltage = 110% of nominal (253V) Frequency = 51,5Hz Power Factor = 1 Period of test 90 minutes
Connection:	
Limit:	Always connected
Test 4	Voltage = 110% of nominal (253V) Frequency = 52,0Hz Power Factor = 1 Period of test 15 minutes
Connection:	Always connected
Limit:	Always connected
Test 5	Confirm that the Power Generating Module is capable of staying connected to the Distribution Network and operate at rates of change of frequency up to 1 Hzs ⁻¹ as measured over a period of 500ms. Note that this is not expected to be demonstrated on site.
Connection:	Always connected
Limit:	Always connected

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Protection. Voltage tests.						
Phase 1						
Function	Setting		Trip test		No trip test	
	Voltage [V]	Time delay [s]	Voltage [V]	Time delay [s]	Voltage / time	Confirm no trip
U/V	184	2,5	185,1	2,597	188V / 5,0s	No trip
					180V / 2,45s	No trip
O/V stage 1	262,2	1,0	261,6	1,084	258,2V 5,0s	No trip
O/V stage 2	273,7	0,5	273,3	0,583	269,7V 0,95s	No trip
					277,7V 0,45s	No trip
Protection. Voltage tests.						
Phase 2						
Function	Setting		Trip test		No trip test	
	Voltage [V]	Time delay [s]	Voltage [V]	Time delay [s]	Voltage / time	Confirm no trip
U/V	184	2,5	184,7	2,567	188V / 5,0s	No trip
					180V / 2,45s	No trip
O/V stage 1	262,2	1,0	261,4	1,061	258,2V 5,0s	No trip
O/V stage 2	273,7	0,5	273,0	0,560	269,7V 0,95s	No trip
					277,7V 0,45s	No trip

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Protection. Voltage tests.

Phase 3						
Function	Setting		Trip test		No trip test	
	Voltage [V]	Time delay [s]	Voltage [V]	Time delay [s]	Voltage / time	Confirm no trip
U/V	184	2,5	184,7	2,570	188V / 5,0s	No trip
					180V / 2,45s	No trip
O/V stage 1	262,2	1,0	184,7	2,570	258,2V 5,0s	No trip
O/V stage 2	273,7	0,5	273,0	0,587	269,7V 0,95s	No trip
					277,7V 0,45s	No trip

Note. For Voltage tests the Voltage required to trip is the setting $\pm 3,45V$. The time delay can be measured at a larger deviation than the minimum required to operate the protection. The No trip tests need to be carried out at the setting $\pm 4V$ and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

Protection. Frequency tests.

Function	Setting		Trip test		No trip test	
	Frequency [Hz]	Time delay [s]	Frequency [Hz]	Time delay [s]	Frequency / time	Confirm no trip
U/F stage 1	47,5	20	47,50	20,056	47,7Hz / 30s	No trip
U/F stage 2	47	0,5	47,00	0,573	47,2Hz / 19,5s	No trip
					46,8Hz / 0,45s	No trip
O/F stage 2	52	0,5	52,00	0,584	51,8Hz / 120s	No trip
					52,2Hz / 0,45s	No trip

Note. For Frequency Trip tests the Frequency required to trip is the setting $\pm 0,1Hz$. In order to measure the time delay a larger deviation than the minimum required to operate the projection can be used. The "No-trip tests" need to be carried out at the setting $\pm 0,2Hz$ and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Protection. Loss of Mains.

Inverters tested according to BS EN 62116.

Balancing load on islanded network	33% of -5% Q Test 22	66% of -5% Q Test 12	100% of -5% P Test 5	33% of +5% Q Test 31	66% of +5% Q Test 21	100% of +5% P Test 10
Trip time. Ph1 fuse removed [s]	0,348	0,421	0,232	0,342	0,347	0,286
Trip time. Ph2 fuse removed [s]	0,348	0,421	0,232	0,342	0,347	0,286
Trip time. Ph3 fuse removed [s]	0,348	0,421	0,232	0,342	0,347	0,286

Note. Trip time limit is 0,5s.

Protection. Re-connection timer.

Test should prove that the reconnection sequence starts in no less than 20 seconds for restoration of voltage and frequency to within the stage 1 settings of table 10.1.

Over Voltage				
Time delay setting		Measured delay		
20s		64		
Under Voltage				
Time delay setting		Measured delay		
20s		62		
Over Frequency				
Time delay setting		Measured delay		
20s		70		
Under Frequency				
Time delay setting		Measured delay		
20s		70		
	Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of table 1.			
	At 266,2V	At 180,0V	At 47,4Hz	At 52,1Hz
Confirmation that the Generating Unit does not re-connect.	No reconnection	No reconnection	No reconnection	No reconnection

Protection. Frequency change, Stability test.

	Start Frequency [Hz]	Change	Test Duration	Confirm no trip
Positive Vector Shift	49,5	+50 degrees		No trip
Negative Vector Shift	50,5	-50 degrees		No trip
Positive Frequency drift	49,0 to 51,0	+0,95Hz/sec	2,1s	No trip
Negative Frequency drift	51,0 to 49,0	-0,95Hz/sec	2,1s	No trip

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Limited Frequency Sensitive Mode – Over Frequency

1-min mean value [Hz]:	a) 50,00	b) 50,45	c) 50,70	d) 51,15	e) 50,70	f) 50,45	g) 50,00
1. Measurement a) to g): Active power output > 80% P_n							
Frequency [Hz]:	50,00	50,55	50,70	51,15	50,70	50,55	50,00
P_{expected} [kW]:	10,00	9,69	9,39	8,49	9,39	9,69	10,00
P_{measured} [kW]:	10,00	9,69	9,39	8,49	9,39	9,69	10,00
2. Measurement a) to g): Active power output 40% and 60% P_n							
Frequency [Hz]:	50,00	50,55	50,70	51,15	50,70	50,55	50,00
P_{expected} [kW]:	5,01	4,86	4,71	4,26	4,71	4,86	5,01
P_{measured} [kW]:	5,01	4,86	4,71	4,26	4,71	4,86	5,01

Output Power with falling Frequency

Frequency setpoint [Hz]:	50,00	49,50	49,00	48,00	47,60	47,10
Frequency [Hz]:	50,00	49,50	49,00	48,00	47,60	47,10
Active power [kW]:	10,00	10,00	10,00	10,00	9,99	9,99
ΔP/P_{max} [%]:		0,00	0,00	0,00	0,06	0,06

Note.

Electronic inverter no power reduction take place.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Harmonics.

PLENTICORE BI 10/26, Phase 1

SSEG rating per phase (rpp)						
At 45-55% of rated output 1665W			100% of rated output 3118W			
Harmonic	Measured Value (MV) in [A]	Measured Value (%) in [A]	Measured Value (MV) in [A]	Measured Value (%) in [A]	Limit in BS EN61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2nd	0,023	0,158	0,034	0,239	1,080	
3rd	0,015	0,105	0,028	0,198	2,300	
4th	0,007	0,048	0,022	0,154	0,430	
5th	0,021	0,146	0,038	0,263	1,140	
6th	0,010	0,073	0,005	0,034	0,300	
7th	0,050	0,350	0,046	0,319	0,770	
8th	0,011	0,077	0,013	0,089	0,230	
9th	0,017	0,120	0,018	0,128	0,400	
10th	0,006	0,039	0,003	0,023	0,184	
11th	0,022	0,152	0,024	0,166	0,330	
12th	0,009	0,065	0,003	0,023	0,153	
13th	0,016	0,111	0,045	0,313	0,210	
14th	0,014	0,100	0,010	0,067	0,131	
15th	0,004	0,029	0,006	0,042	0,150	
16th	0,012	0,080	0,004	0,025	0,115	
17th	0,021	0,147	0,037	0,259	0,132	
18th	0,006	0,038	0,005	0,035	0,102	
19th	0,029	0,199	0,022	0,154	0,118	
20th	0,005	0,033	0,005	0,038	0,092	
21th	0,009	0,060	0,006	0,041	0,107	0,160
22th	0,006	0,041	0,006	0,039	0,084	
23th	0,035	0,244	0,017	0,117	0,098	0,147
24th	0,007	0,046	0,006	0,040	0,077	
25th	0,039	0,268	0,017	0,116	0,090	0,135
26th	0,009	0,060	0,013	0,091	0,071	
27th	0,008	0,053	0,006	0,043	0,083	0,124
28th	0,004	0,025	0,005	0,037	0,066	
29th	0,018	0,123	0,023	0,158	0,078	0,117
30th	0,004	0,029	0,004	0,029	0,061	
31th	0,015	0,106	0,018	0,127	0,073	0,109
32th	0,007	0,048	0,005	0,033	0,058	
33th	0,004	0,025	0,006	0,040	0,068	0,102
34th	0,005	0,036	0,003	0,021	0,054	
35th	0,011	0,078	0,011	0,074	0,064	0,096
36th	0,002	0,014	0,003	0,018	0,051	
37th	0,005	0,036	0,018	0,122	0,061	0,091
38th	0,005	0,032	0,005	0,035	0,048	
39th	0,004	0,026	0,002	0,016	0,058	0,087
40th	0,004	0,028	0,002	0,014	0,046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Harmonics.

PLENTICORE BI 10/26, Phase 2

SSEG rating per phase (rpp)						
At 45-55% of rated output 1665W			100% of rated output 3337W			
Harmonic	Measured Value (MV) in [A]	Measured Value (%) in [A]	Measured Value (MV) in [A]	Measured Value (%) in [A]	Limit in BS EN61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2nd	0,023	0,158	0,034	0,239	1,080	
3rd	0,015	0,105	0,028	0,198	2,300	
4th	0,007	0,048	0,022	0,154	0,430	
5th	0,021	0,146	0,038	0,263	1,140	
6th	0,010	0,073	0,005	0,034	0,300	
7th	0,050	0,350	0,046	0,319	0,770	
8th	0,011	0,077	0,013	0,089	0,230	
9th	0,017	0,120	0,018	0,128	0,400	
10th	0,006	0,039	0,003	0,023	0,184	
11th	0,022	0,152	0,024	0,166	0,330	
12th	0,009	0,065	0,003	0,023	0,153	
13th	0,016	0,111	0,045	0,313	0,210	
14th	0,014	0,100	0,010	0,067	0,131	
15th	0,004	0,029	0,006	0,042	0,150	
16th	0,012	0,080	0,004	0,025	0,115	
17th	0,021	0,147	0,037	0,259	0,132	
18th	0,006	0,038	0,005	0,035	0,102	
19th	0,029	0,199	0,022	0,154	0,118	
20th	0,005	0,033	0,005	0,038	0,092	
21th	0,009	0,060	0,006	0,041	0,107	0,160
22th	0,006	0,041	0,006	0,039	0,084	
23th	0,035	0,244	0,017	0,117	0,098	0,147
24th	0,007	0,046	0,006	0,040	0,077	
25th	0,039	0,268	0,017	0,116	0,090	0,135
26th	0,009	0,060	0,013	0,091	0,071	
27th	0,008	0,053	0,006	0,043	0,083	0,124
28th	0,004	0,025	0,005	0,037	0,066	
29th	0,018	0,123	0,023	0,158	0,078	0,117
30th	0,004	0,029	0,004	0,029	0,061	
31th	0,015	0,106	0,018	0,127	0,073	0,109
32th	0,007	0,048	0,005	0,033	0,058	
33th	0,004	0,025	0,006	0,040	0,068	0,102
34th	0,005	0,036	0,003	0,021	0,054	
35th	0,011	0,078	0,011	0,074	0,064	0,096
36th	0,002	0,014	0,003	0,018	0,051	
37th	0,005	0,036	0,018	0,122	0,061	0,091
38th	0,005	0,032	0,005	0,035	0,048	
39th	0,004	0,026	0,002	0,016	0,058	0,087
40th	0,004	0,028	0,002	0,014	0,046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Harmonics.

PLENTICORE BI 10/26, Phase 3

SSEG rating per phase (rpp)						
At 45-55% of rated output 1690W			100% of rated output 3369W			
Harmonic	Measured Value (MV) in [A]	Measured Value (%) in [A]	Measured Value (MV) in [A]	Measured Value (%) in [A]	Limit in BS EN61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2nd	0,014	0,095	0,032	0,220	1,080	
3rd	0,014	0,097	0,020	0,137	2,300	
4th	0,011	0,078	0,025	0,169	0,430	
5th	0,014	0,093	0,043	0,294	1,140	
6th	0,032	0,221	0,005	0,034	0,300	
7th	0,047	0,322	0,031	0,210	0,770	
8th	0,004	0,029	0,011	0,076	0,230	
9th	0,004	0,026	0,004	0,026	0,400	
10th	0,008	0,056	0,003	0,020	0,184	
11th	0,014	0,098	0,034	0,234	0,330	
12th	0,016	0,109	0,004	0,025	0,153	
13th	0,031	0,213	0,035	0,236	0,210	
14th	0,018	0,121	0,009	0,059	0,131	
15th	0,004	0,028	0,007	0,048	0,150	
16th	0,011	0,075	0,004	0,028	0,115	
17th	0,023	0,157	0,035	0,238	0,132	
18th	0,004	0,029	0,005	0,037	0,102	
19th	0,027	0,184	0,023	0,159	0,118	
20th	0,006	0,043	0,008	0,053	0,092	
21th	0,011	0,073	0,005	0,033	0,107	0,160
22th	0,004	0,027	0,008	0,055	0,084	
23th	0,036	0,249	0,012	0,081	0,098	0,147
24th	0,007	0,050	0,004	0,025	0,077	
25th	0,037	0,252	0,020	0,133	0,090	0,135
26th	0,007	0,049	0,011	0,073	0,071	
27th	0,008	0,053	0,003	0,019	0,083	0,124
28th	0,006	0,043	0,004	0,027	0,066	
29th	0,018	0,120	0,022	0,151	0,078	0,117
30th	0,003	0,018	0,002	0,016	0,061	
31th	0,018	0,122	0,016	0,110	0,073	0,109
32th	0,007	0,046	0,004	0,027	0,058	
33th	0,003	0,022	0,004	0,025	0,068	0,102
34th	0,005	0,037	0,005	0,032	0,054	
35th	0,012	0,080	0,013	0,087	0,064	0,096
36th	0,003	0,023	0,002	0,016	0,051	
37th	0,006	0,040	0,014	0,094	0,061	0,091
38th	0,004	0,027	0,005	0,033	0,048	
39th	0,003	0,019	0,004	0,026	0,058	0,087
40th	0,003	0,022	0,002	0,014	0,046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Harmonics.

PLENTICORE BI 5.5/26, Phase 1

SSEG rating per phase (rpp)						
At 45-55% of rated output 1665W			100% of rated output 3118W			
Harmonic	Measured Value (MV) in [A]	Measured Value (%) in [A]	Measured Value (MV) in [A]	Measured Value (%) in [A]	Limit in BS EN61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2nd	0,030	0,390	0,020	0,257	1,080	
3rd	0,045	0,578	0,042	0,541	2,300	
4th	0,031	0,401	0,035	0,450	0,430	
5th	0,021	0,267	0,064	0,821	1,140	
6th	0,025	0,324	0,012	0,149	0,300	
7th	0,045	0,579	0,062	0,794	0,770	
8th	0,015	0,197	0,032	0,408	0,230	
9th	0,007	0,091	0,014	0,175	0,400	
10th	0,014	0,185	0,022	0,278	0,184	
11th	0,042	0,534	0,013	0,167	0,330	
12th	0,018	0,226	0,012	0,149	0,153	
13th	0,046	0,588	0,016	0,210	0,210	
14th	0,014	0,179	0,044	0,561	0,131	
15th	0,053	0,675	0,017	0,224	0,150	
16th	0,041	0,527	0,038	0,490	0,115	
17th	0,068	0,864	0,066	0,850	0,132	
18th	0,066	0,849	0,027	0,348	0,102	
19th	0,075	0,961	0,054	0,696	0,118	
20th	0,071	0,906	0,044	0,567	0,092	
21th	0,040	0,514	0,021	0,264	0,107	0,160
22th	0,052	0,670	0,042	0,543	0,084	
23th	0,025	0,321	0,021	0,269	0,098	0,147
24th	0,019	0,246	0,016	0,204	0,077	
25th	0,009	0,112	0,046	0,585	0,090	0,135
26th	0,016	0,207	0,016	0,205	0,071	
27th	0,010	0,123	0,006	0,070	0,083	0,124
28th	0,019	0,248	0,005	0,068	0,066	
29th	0,014	0,181	0,021	0,269	0,078	0,117
30th	0,004	0,054	0,003	0,038	0,061	
31th	0,007	0,095	0,018	0,234	0,073	0,109
32th	0,007	0,088	0,006	0,075	0,058	
33th	0,003	0,035	0,004	0,055	0,068	0,102
34th	0,013	0,168	0,007	0,088	0,054	
35th	0,005	0,063	0,009	0,116	0,064	0,096
36th	0,003	0,043	0,003	0,037	0,051	
37th	0,006	0,080	0,007	0,092	0,061	0,091
38th	0,004	0,055	0,005	0,064	0,048	
39th	0,005	0,067	0,003	0,034	0,058	0,087
40th	0,005	0,066	0,007	0,083	0,046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Harmonics.

PLENTICORE BI 5.5/26, Phase 2

SSEG rating per phase (rpp)						
At 45-55% of rated output 919W			100% of rated output 1826W			
Harmonic	Measured Value (MV) in [A]	Measured Value (%) in [A]	Measured Value (MV) in [A]	Measured Value (%) in [A]	Limit in BS EN61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2nd	0,016	0,207	0,016	0,199	1,080	
3rd	0,017	0,216	0,015	0,191	2,300	
4th	0,018	0,226	0,017	0,216	0,430	
5th	0,020	0,251	0,058	0,739	1,140	
6th	0,016	0,204	0,009	0,115	0,300	
7th	0,017	0,213	0,047	0,605	0,770	
8th	0,013	0,164	0,025	0,326	0,230	
9th	0,014	0,184	0,007	0,092	0,400	
10th	0,011	0,142	0,013	0,166	0,184	
11th	0,053	0,675	0,015	0,188	0,330	
12th	0,019	0,245	0,008	0,108	0,153	
13th	0,027	0,341	0,010	0,125	0,210	
14th	0,032	0,405	0,030	0,389	0,131	
15th	0,018	0,230	0,014	0,182	0,150	
16th	0,017	0,220	0,024	0,309	0,115	
17th	0,032	0,406	0,049	0,625	0,132	
18th	0,026	0,327	0,020	0,261	0,102	
19th	0,039	0,504	0,029	0,371	0,118	
20th	0,058	0,746	0,032	0,411	0,092	
21th	0,024	0,313	0,014	0,181	0,107	0,160
22th	0,019	0,245	0,027	0,339	0,084	
23th	0,015	0,186	0,025	0,323	0,098	0,147
24th	0,011	0,146	0,011	0,137	0,077	
25th	0,019	0,248	0,037	0,470	0,090	0,135
26th	0,014	0,184	0,013	0,161	0,071	
27th	0,006	0,082	0,008	0,104	0,083	0,124
28th	0,019	0,247	0,006	0,074	0,066	
29th	0,015	0,189	0,020	0,252	0,078	0,117
30th	0,004	0,048	0,003	0,036	0,061	
31th	0,003	0,041	0,020	0,252	0,073	0,109
32th	0,004	0,053	0,007	0,094	0,058	
33th	0,003	0,042	0,004	0,049	0,068	0,102
34th	0,012	0,152	0,007	0,085	0,054	
35th	0,005	0,068	0,013	0,160	0,064	0,096
36th	0,003	0,043	0,002	0,027	0,051	
37th	0,004	0,047	0,008	0,102	0,061	0,091
38th	0,003	0,039	0,005	0,067	0,048	
39th	0,004	0,051	0,002	0,032	0,058	0,087
40th	0,004	0,050	0,005	0,063	0,046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Harmonics.

PLENTICORE BI 5.5/26, Phase 3

SSEG rating per phase (rpp)						
At 45-55% of rated output 919W			100% of rated output 1819W			
Harmonic	Measured Value (MV) in [A]	Measured Value (%) in [A]	Measured Value (MV) in [A]	Measured Value (%) in [A]	Limit in BS EN61000-3-2 in Amps	Higher limit for odd harmonics 21 and above
2nd	0,038	0,488	0,027	0,345	1,080	
3rd	0,028	0,365	0,025	0,318	2,300	
4th	0,026	0,333	0,024	0,310	0,430	
5th	0,013	0,167	0,070	0,896	1,140	
6th	0,031	0,394	0,005	0,066	0,300	
7th	0,033	0,426	0,045	0,579	0,770	
8th	0,013	0,169	0,022	0,286	0,230	
9th	0,008	0,104	0,005	0,070	0,400	
10th	0,007	0,090	0,016	0,203	0,184	
11th	0,045	0,571	0,013	0,169	0,330	
12th	0,009	0,115	0,007	0,090	0,153	
13th	0,044	0,570	0,018	0,233	0,210	
14th	0,040	0,517	0,034	0,442	0,131	
15th	0,033	0,423	0,009	0,111	0,150	
16th	0,029	0,369	0,018	0,235	0,115	
17th	0,035	0,449	0,049	0,634	0,132	
18th	0,041	0,529	0,011	0,147	0,102	
19th	0,041	0,524	0,041	0,524	0,118	
20th	0,033	0,430	0,024	0,308	0,092	
21th	0,025	0,322	0,015	0,196	0,107	0,160
22th	0,039	0,506	0,041	0,524	0,084	
23th	0,015	0,198	0,012	0,157	0,098	0,147
24th	0,013	0,163	0,008	0,103	0,077	
25th	0,027	0,349	0,052	0,664	0,090	0,135
26th	0,018	0,226	0,009	0,118	0,071	
27th	0,006	0,073	0,003	0,043	0,083	0,124
28th	0,016	0,205	0,006	0,079	0,066	
29th	0,008	0,105	0,014	0,186	0,078	0,117
30th	0,005	0,062	0,003	0,039	0,061	
31th	0,006	0,073	0,022	0,285	0,073	0,109
32th	0,007	0,092	0,009	0,116	0,058	
33th	0,005	0,059	0,004	0,048	0,068	0,102
34th	0,009	0,110	0,006	0,075	0,054	
35th	0,002	0,031	0,009	0,118	0,064	0,096
36th	0,003	0,040	0,003	0,033	0,051	
37th	0,009	0,111	0,008	0,107	0,061	0,091
38th	0,004	0,054	0,004	0,052	0,048	
39th	0,004	0,048	0,002	0,028	0,058	0,087
40th	0,003	0,037	0,006	0,077	0,046	

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Power factor.				
PLENTICORE BI 10/26				
Output power	216,2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within ±1,5% of the stated level during the test.
20%	0,999	0,999	0,999	
50%	0,999	0,999	0,999	
75%	0,999	0,999	0,999	
100%	0,999	0,999	0,999	
Limit	>0,95	>0,95	>0,95	
PLENTICORE BI 5.5/26				
Output power	216,2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within ±1,5% of the stated level during the test.
20%	0,999	0,999	0,999	
50%	0,999	0,999	0,999	
75%	0,999	0,999	0,999	
100%	0,999	0,999	0,999	
Limit	>0,95	>0,95	>0,95	

Power Quality. Voltage fluctuation and Flicker.								
PLENTICORE BI 10.0/26								
	Starting			Stopping			Running	
	dmax	dc	d(t)	dmax	dc	d(t)	Pst	Plt 2 hours
Measured values at test impedance	0,870	0,850	0,000	0,870	0,850	0,000	0,192	0,151
Measured values at standard impedance	0,870	0,850	0,000	0,870	0,850	0,000	0,192	0,151
Values for maximum impedance	3,378	3,300	0,000	3,378	3,300	0,000	0,745	0,585
Limits set under BS EN 61000-3-11	4%	3,3%	3,3% 500ms	4%	3,3%	3,3% 500ms	1,0	0,65
Test impedance	R	0,24	Ω	XI	0,15	Ω		
	Z	0,28	Ω					
Standard impedance	R	0,24	Ω	XI	0,15	Ω		
	Z	0,28	Ω					
Maximum impedance	R	0,93	Ω	XI	0,58	Ω		
	Zmax	1,10	Ω					

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. Voltage fluctuation and Flicker.
PLENTICORE BI 5.5/26

	Starting			Stopping			Running	
	dmax	dc	d(t)	dmax	dc	d(t)	Pst	Plt 2 hours
Measured values at test impedance	0,870	0,850	0,000	0,870	0,850	0,000	0,192	0,129
Measured values at standard impedance	0,870	0,850	0,000	0,870	0,850	0,000	0,192	0,129
Values for maximum impedance	3,378	3,300	0,000	3,378	3,300	0,000	0,745	0,501
Limits set under BS EN 61000-3-11	4%	3,3%	3,3% 500ms	4%	3,3%	3,3% 500ms	1,0	0,65
Test impedance	R	0,24	Ω	XI		0,15	Ω	
	Z	0,28	Ω					
Standard impedance	R	0,24	Ω	XI		0,15	Ω	
	Z	0,28	Ω					
Maximum impedance	R	0,93	Ω	XI		0,58	Ω	
	Zmax	1,10	Ω					

Power Quality. DC injection.
PLENTICORE BI 10/26
Phase 1

Test level power [%]	10	55	100
Recorded value [mA]	19	15	11
Recorded value [%]	0,12	0,09	0,07
Limit [%]	0,25	0,25	0,25

Phase 2

Test level power [%]	10	55	100
Recorded value [mA]	9	8	3
Recorded value [%]	0,06	0,05	0,02
Limit [%]	0,25	0,25	0,25

Phase 3

Test level power [%]	10	55	100
Recorded value [mA]	11	15	19
Recorded value [%]	0,07	0,09	0,12
Limit [%]	0,25	0,25	0,25

Note. DC-injection is tested at each phase of the inverter and a limit of 0,25% per phase was used as pass criteria.

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Power Quality. DC injection.			
PLENTICORE BI 5.5/26			
Phase 1			
Test level power [%]	10	55	100
Recorded value [mA]	10	13	9
Recorded value [%]	0,11	0,15	0,10
Limit [%]	0,25	0,25	0,25
Phase 2			
Test level power [%]	10	55	100
Recorded value [mA]	8	7	4
Recorded value [%]	0,09	0,08	0,05
Limit [%]	0,25	0,25	0,25
Phase 3			
Test level power [%]	10	55	100
Recorded value [mA]	15	8	17
Recorded value [%]	0,17	0,09	0,19
Limit [%]	0,25	0,25	0,25
Note. DC-injection is tested at each phase of the inverter and a limit of 0,25% per phase was used as pass criteria.			

Fault level Contribution. Phase 1					
For a directly coupled SSEG			For a Inverter SSEG		
Parameter	Symbol	Value	Time after fault	Volts [V]	Amps [A]
Peak Short Circuit current	I_p	N/A	20ms	8,6	4,17
Initial Value of aperiodic current	A	N/A	100ms	7,3	1,96
Initial symmetrical short-circuit current*	I_k	N/A	250ms	7,1	1,25
Decaying (aperiodic) component of short circuit current*	i_{DC}	N/A	500ms	7,0	0,89
Reactance/Resistance Ratio of source*	X/R	N/A	Time to Trip [s]	2,568	In seconds
Fault level Contribution. Phase 2					
For a directly coupled SSEG			For a Inverter SSEG		
Parameter	Symbol	Value	Time after fault	Volts [V]	Amps [A]
Peak Short Circuit current	I_p	N/A	20ms	8,3	2,93
Initial Value of aperiodic current	A	N/A	100ms	7,8	1,40
Initial symmetrical short-circuit current*	I_k	N/A	250ms	7,5	0,90
Decaying (aperiodic) component of short circuit current*	i_{DC}	N/A	500ms	7,2	0,64
Reactance/Resistance Ratio of source*	X/R	N/A	Time to Trip [s]	2,568	In seconds

Appendix A2-3 Compliance Verification Report for Inverter Connected Power Generating Modules

Extract from test report according to the Engineering Recommendation G99

Nr. 19TH0374-BI-G99/1_0

Fault level Contribution. Phase 3

For a directly coupled SSEG			For a Inverter SSEG		
Parameter	Symbol	Value	Time after fault	Volts [V]	Amps [A]
Peak Short Circuit current	I_p	N/A	20ms	8,5	5,40
Initial Value of aperiodic current	A	N/A	100ms	7,8	2,43
Initial symmetrical short-circuit current*	I_k	N/A	250ms	7,4	1,56
Decaying (aperiodic) component of short circuit current*	i_{DC}	N/A	500ms	7,2	1,11
Reactance/Resistance Ratio of source*	X/R	N/A	Time to Trip [s]	2,568	In seconds

For rotating machines and linear piston machines the test should produce a 0s – 2s plot of the short circuit current as seen at the Generating Unit terminals.

* Values for these parameters should be provided where the short circuit duration is sufficiently long to enable interpolation of the plot.

Self Monitoring – Solid state switching.	N/A
It has been verified that in the event of the solid state switching device failing to disconnect the Power Park Module, the voltage on the output side of the switching device is reduced to a value below 50 volts within 0,5 seconds.	N/A
Note. Unit do not provide solid state switching relays. In case the semiconductor bridge is switched off, then the voltage on the output drops to 0. In this case the relays on the output will also open (Functional safety of the internal automatic disconnection device according to VDE 0126-1-1).	

Wiring functional tests if required by para. 15.2.1	N/A
Type test of components wired correct together on site is part of the commissioning test.	

Logic Interface (input port)	P
Confirm that an input port is provided and can be used to shut down the module.	Yes

Additional comments