

PLENTICORE G3

with battery



Technical Specification

PLENTICORE G3



PLENTICORE G3			S			M			L			
Input side (DC)	Basic power	kW	4.0			8.5			15			
	Optional power upgrade level 1 ¹⁾	kW		5.5			10			17.5		
	Optional power upgrade level 2 ¹⁾	kW			7.0			12.5			20	
	Max. PV power (cos φ = 1)	kWp	6	8.25	10.25	12.75	15	18.75	22.5	26.5	30	
	Max. PV power per DC input	kW	8.25	8.25	8.25	10.5	10.5	10.5	18	18	18	
	Nominal DC power	kW	4.08	5.61	7.14	8.67	10.2	12.75	15.3	17.85	20.4	
	Start-up input voltage (U _{DCstart})	V	95									
	Max. system voltage (U _{DCmax})	V	1000									
	MPP range at rated output (U _{MPPmin}) ³⁾	V	80	110	140	170	200	250	170	198	227	
	MPP range at rated output (U _{MPPmax}) ³⁾	V	800	800	800	800	800	800	800	800	800	
	Working voltage range (U _{DCworkmin} - U _{DCworkmax}) ⁴⁾	V	75...900									
	Max. input current (I _{DCmax}) DC1/DC2 input	A	17			17			30			
	Max. input current (I _{DCmax}) DC3 input	A	17			30			30			
	Number of DC inputs		3									
	Number of combined DC inputs (PV or battery)		1									
	Number of independent MPP trackers		3									
	DC 3 - Batterieeingang optional											
	Min. Working voltage for battery input (U _{DCworkbatmin})	V	95									
	Max. Working voltage for battery input (U _{DCworkbatmax})	V	650									
	Max. charging/discharging current at battery input	A	17/17			30/30			30/30			
Output side (AC)	Rated power, cos φ = 1 (P _{AC,r})	kW	4.0	5.5	7.0	8.5	10	12.5	15	17.5	20	
	Apparent output power (S _{AC,Nom} / S _{AC,max})	kVA	4.0/ 4.0	5.5/ 5.5	7.0/ 7.0	8.5/ 8.5	10/ 10	12.5/ 12.5	15/ 15	17.5/ 17.5	20/ 20	
	Min. Output voltage (U _{ACmin})	V	320									
	Max. Output voltage (U _{ACmax})	V	460									
	Max. output current (I _{ACmax})	A	11.2			20			32			
	Grid connection		3N~, 230/400V, 50Hz									
	Standby	W	3.5									
Backupoperation	Backup power operation		3N~, 230/400V, 51 Hz									
	Nominal output power ²⁾	kW	7.0			12.5			20			
	Nominal power per phase	kW	2.33			4.16			6.66			
	Max. output current per phase	A	11.2			20			32			
	Start time with manual KOSTAL BackUp Switch	s	<5									
	Start time with automatic backup box	s	<30									
System data	Operating hours in backup mode	h	5000									
	Max. efficiency	%	98.03			98.14			98.21			
	European efficiency	%	97.20			97.49			97.72			
	Protection class according to IEC 60529		IP 65									
	Height/width/depth	mm	561 / 409 / 237									
	Weight	kg	21.8			22.3			24.3			
	Ambient temperature	°C	-20...60									
	Connection technology, DC side		SUNCLIX plug									
	Directives/Certification ²⁾		CE, GS, CEI 0-21, C10/11, EN 62109-1, EN 62109-2, EN 60529, EN 50438, EN 50549-1, NA/EEA, G98, G99, EIFS2018, IEC 61727, IEC 62116, RD 1699, RD 647, RFG, TOR Erzeuger, UNE 206006, UNE 206007-1, VDE 0126-1-1, VDE-AR-N 4105, VDE-AR-N 4110, VJV2018									

¹⁾ Optional battery and power extension available for a fee from your wholesaler.

²⁾ Nominal output power: The actual output power depends on the system and storage size.

³⁾ MPP range at nominal power: Outside the MPP range, MPP control takes place below the nominal power. Based on full occupancy of all MPP trackers.

⁴⁾ Working voltage range: No feed-in takes place outside the working voltage range.

PLENTICORE G3 with AXITEC AXIstorage Li SV1



AXITEC AXIstorage Li SV1			SV1 10.1 ³⁾	SV1 13.5 ³⁾	SV1 16.9 ³⁾	SV1 20.2 ³⁾	SV1 23.6 ³⁾
System data	Modul type		Li-Ion LFP 3.552 kWh, 48 V, 74 Ah, 36 kg				
	Max. Charging/discharging current battery system	A	40/40				
	Max. Charging/discharging current battery input PLENTICORE S G3	A	17/17				
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	2.4	3.3	4.0	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	2.4	3.3	4.1	4.9 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	2.4	3.3	4.1	4.9 ²⁾	5.7 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30				
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30				
	Max. Power consumption with PLENTICORE L G3 - 15	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	10.1	13.5	16.9	20.2	23.6
	Usable capacity 100% DoD ¹⁾	kWh	10.7	14.2	17.8	21.3	24.9
	Number of battery modules		3	4	5	6	7
	Nominal voltage	V	144	192	240	288	336
	Voltage range	V	130.5-162	174-216	217.5-270	261-324	304.5-378
	Interface to inverter		RS485				
	Height	mm	700	870	1040	1210	1380
	Width/depth	mm	600/380				
	Weight	kg	122	158	194	230	266
	Ambient temperature	°C	0...50				
	IP protection class		IP 55				
	Certification / Safety Standard		VDE2510-50, IEC62619, IEC62477-1, IEC62040-1, CEC, CE, UN38.3, EN 61000-6-2, EN 61000-6-3				

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

3) Axitec AXIstorage Li SV1 battery compatible with BMS module: Li SV1 BMS with article number: AY10785

PLENTICORE G3 with AXITEC AXIstorage Li SV2



AXITEC AXIstorage Li SV2		SV2 6.7 ³⁾	SV2 10.1 ³⁾	SV2 13.5 ³⁾	SV2 16.9 ³⁾
System data	Modul type	Li-Ion LFP 3.552 kWh, 96 V, 37 Ah, 35 kg			
	Max. Charging/discharging current battery system	A			
	Max. Charging/discharging current battery input PLENTICORE S G3	A			
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	3.3	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	3.3 ²⁾	4.9 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	3.3 ²⁾	4.9 ²⁾	6.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30		
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	5.8 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	5.8 ²⁾	8.6 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	5.8 ²⁾	8.6 ²⁾	10.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30		
	Max. Power consumption with PLENTICORE L G3 - 15	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	6.7	10.1	13.5
	Usable capacity 100% DoD ¹⁾	kWh	7.1	10.7	14.2
	Number of battery modules		2	3	4
	Nominal voltage	V	192	288	384
	Voltage range	V	174-216	261-324	261-324
	Interface to inverter		RS485		
	Height	mm	822	1118	1414
	Width/depth	mm	450/296		
	Weight	kg	82	117	152
	Ambient temperature	°C	0...50		
	IP protection class		IP 55		
	Certification / Safety Standard		VDE2510-50, IEC62619, IEC62477-1, IEC62040-1, CEC, CE, UN38.3, EN 61000-6-2, EN 61000-6-3		

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

3) Axitec AXIstorage Li SV2 battery compatible with BMS module: Li SV2 BMS with article number: AY10786

PLENTICORE G3 with BYD Battery-Box HV



BYD Battery-Box HV		H 6.4	H 7.7	H 9.0	H 10.2	H 11.5
Modul type		HV (High Voltage) 51.2 V, 25 Ah, 1.28 kWh, 25 kg, LiFePO ₄				
Max. Charging/discharging current battery system	A	25/25				
Max. Charging/discharging current battery input PLENTICORE S G3	A	17/17				
Max. Power consumption with PLENTICORE S G3 - 4.0	kW	4.0	4.0	4.0	4.0	4.0
Max. Power consumption with PLENTICORE S G3 - 5.5	kW	4.4 ²⁾	5.2 ²⁾	5.5 ²⁾	5.5 ²⁾	5.5 ²⁾
Max. Power consumption with PLENTICORE S G3 - 7.0	kW	4.4 ²⁾	5.2 ²⁾	6.1 ²⁾	7.0 ²⁾	7.0 ²⁾
Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30				
Max. Power consumption with PLENTICORE M G3 - 8.5	kW	6.4 ²⁾	7.7 ²⁾	8.5 ²⁾	8.5 ²⁾	8.5 ²⁾
Max. Power consumption with PLENTICORE M G3 - 10	kW	6.4 ²⁾	7.7 ²⁾	9.0 ²⁾	10.0 ²⁾	10.0 ²⁾
Max. Power consumption with PLENTICORE M G3 - 12.5	kW	6.4 ²⁾	7.7 ²⁾	9.0 ²⁾	10.2 ²⁾	10.5 ²⁾
Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30				
Max. Power consumption with PLENTICORE L G3 - 15	kW	6.4 ²⁾	7.7 ²⁾	9.0 ²⁾	10.2 ²⁾	11.5 ²⁾
Max. Power consumption with PLENTICORE L G3 - 17.5	kW	6.4 ²⁾	7.7 ²⁾	9.0 ²⁾	10.2 ²⁾	11.5 ²⁾
Max. Power consumption with PLENTICORE L G3 - 20	kW	6.4 ²⁾	7.7 ²⁾	9.0 ²⁾	10.2 ²⁾	11.5 ²⁾
Usable capacity 95% DoD ¹⁾	kWh	6.1	7.3	8.6	9.7	10.9
Usable capacity 100% DoD ¹⁾	kWh	6.4	7.7	9.0	10.2	11.5
Number of battery modules		5	6	7	8	9
Nominal voltage	V	256	307	358	409	460
Voltage range	V	200-282	240-338	280-395	320-451	360-500
Interface to inverter		RS485				
Height	mm	894	1014	1134	1254	1374
Width/depth	mm	580/380				
Weight	kg	148	174	200	226	252
Ambient temperature	°C	-10...50				
IP protection class		IP 55				
Certification / Safety Standard		CE, UL1642, TÜV (IEC62619), RCM, UN38.3				

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

PLENTICORE G3 with BYD Battery-Box Premium HVS/HVM



BYD Battery-Box Premium			HVS 5.1	HVS 7.7	HVS 10.2	HVS 12.8	HVM 8.3	HVM 11.0	HVM 13.8	HVM 16.6	HVM 19.3	HVM 22.1
System data	Modul type		LiFePO4 2.56kWh, 102.4V, 25Ah, 38kg				LiFePO4 2.76kWh, 51.2V, 53Ah, 38kg,					
	Max. Charging/discharging current battery system	A	25/25				50/50					
	Max. Charging/discharging current battery input PLENTICORE S G3	A	17/17									
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	3.5	4.0	4.0	4.0	2.6	3.5	4.0	4.0	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	3.5	5.2 ²⁾	5.5 ²⁾	5.5 ²⁾	2.6	3.5	4.4 ²⁾	5.5 ²⁾	5.5 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	3.5	5.2 ²⁾	7.0 ²⁾	7.0 ²⁾	2.6	3.5	4.4 ²⁾	6.1 ²⁾	7.0 ²⁾	7.0 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30									
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	5.1 ²⁾	7.7 ²⁾	8.5 ²⁾	8.5 ²⁾	4.6 ²⁾	6.1 ²⁾	7.7 ²⁾	8.5 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	5.1 ²⁾	7.7 ²⁾	10.0 ²⁾	10.0 ²⁾	4.6 ²⁾	6.1 ²⁾	7.7 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	5.1 ²⁾	7.7 ²⁾	10.2 ²⁾	10.5 ²⁾	4.6 ²⁾	6.1 ²⁾	7.7 ²⁾	10.1 ²⁾	10.5 ²⁾	10.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30									
	Max. Power consumption with PLENTICORE L G3 - 15	kW	5.1 ²⁾	7.7 ²⁾	10.2 ²⁾	12.8 ²⁾	4.6 ²⁾	6.1 ²⁾	7.7 ²⁾	9.2 ²⁾	10.7 ²⁾	12.3 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	5.1 ²⁾	7.7 ²⁾	10.2 ²⁾	12.8 ²⁾	4.6 ²⁾	6.1 ²⁾	7.7 ²⁾	9.2 ²⁾	10.7 ²⁾	12.3 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	5.1 ²⁾	7.7 ²⁾	10.2 ²⁾	12.8 ²⁾	4.6 ²⁾	6.1 ²⁾	7.7 ²⁾	9.2 ²⁾	10.7 ²⁾	12.3 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	4.9	7.3	9.7	12.2	7.9	10.5	13.1	15.7	18.4	21.0
	Usable capacity 100% DoD ¹⁾	kWh	5.1	7.7	10.2	12.8	8.3	11.0	13.8	16.6	19.3	22.1
	Number of battery modules		2	3	4	5	3	4	5	6	7	8
	Nominal voltage	V	204	307	409	512	153	204	256	307	358	409
	Voltage range	V	160-240	240-360	320-480	400-600	120-180	160-240	200-300	240-360	280-420	320-480
	Interface to inverter		RS485									
Height	mm	712	945	1178	1411	945	1178	1411	1644	1877	2110	
Width/depth	mm	585/298										
Weight	kg	91	129	167	205	129	167	205	243	281	319	
Ambient temperature	°C	-10...50										
IP protection class		IP 55										
Certification / Safety Standard		VDE2510-50 / IEC62619 / CEC / CE / UN38.3										

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

PLENTICORE G3 with Dyness Tower



Dyness Tower		T7	T10	T14	T17	T21
System data	Modul type	Li-Ion LFP 3.552 kWh, 96 V, 37 Ah, 41 kg				
	Max. Charging/discharging current battery system	A				
	Max. Charging/discharging current battery input PLENTICORE S G3	17/17				
	Max. Power consumption with PLENTICORE S G3 - 4.0	3.3	4.0	4.0	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	3.3	4.9 ²⁾	5.5 ²⁾	5.5 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	3.3	4.9 ²⁾	6.5 ²⁾	7.0 ²⁾	7.0 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	30/30				
	Max. Power consumption with PLENTICORE M G3 - 8.5	4.3 ²⁾	6.4 ²⁾	8.5 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	4.3 ²⁾	6.4 ²⁾	8.5 ²⁾	10.0 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	4.3 ²⁾	6.4 ²⁾	8.5 ²⁾	10.5 ²⁾	10.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	30/30				
	Max. Power consumption with PLENTICORE L G3 - 15	4.3 ²⁾	6.4 ²⁾	8.5 ²⁾	10.7 ²⁾	12.7 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	4.3 ²⁾	6.4 ²⁾	8.5 ²⁾	10.7 ²⁾	12.7 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	4.3 ²⁾	6.4 ²⁾	8.5 ²⁾	10.7 ²⁾	12.7 ²⁾
	Usable capacity 95% DoD ¹⁾	6.7	10.2	13.5	16.9	20.2
	Usable capacity 100% DoD ¹⁾	7.1	10.7	14.2	17.8	21.3
	Number of battery modules	2	3	4	5	6
	Nominal voltage	192	288	384	480	576
	Voltage range	168-216	252-324	336-432	420-540	504-648
	Interface to inverter	RS485				
	Height	700	900	1100	1300	1500
	Width/depth	504/380				
	Weight	105	146	187	228	269
	Ambient temperature	°C				
	IP protection class	IP54				
	Certification / Safety Standard	IEC 62040-1, IEC 62619, IEC 63056, UL1973, CE, EN 61000-6-1, EN 61000-6-2, EN 61000-6-3, EN 61000-6-4				

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

PLENTICORE G3 with Dyness Tower Pro



Dyness Tower Pro		TP7	TP11	TP15	TP19	TP23
System data	Modul type	LiFePO4 3.84 kWh, 96 V, 40 Ah, 34.5 kg				
	Max. Charging/discharging current battery system	A				
	Max. Charging/discharging current battery input PLENTICORE S G3	A				
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	3.3	4.0	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	3.3	4.9 ²⁾	5.5 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	3.3	4.9 ²⁾	6.5 ²⁾	7.0 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30			
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	5.8 ²⁾	8.5 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	5.8 ²⁾	8.6 ²⁾	10.0 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	5.8 ²⁾	8.6 ²⁾	10.5 ²⁾	10.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30			
	Max. Power consumption with PLENTICORE L G3 - 15	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾	14.4 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾	14.4 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾	14.4 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	7.3	10.9	14.6	18.2
	Usable capacity 100% DoD ¹⁾	kWh	7.7	11.5	15.4	19.2
	Number of battery modules		2	3	4	5
	Nominal voltage	V	192	288	384	480
	Voltage range	V	168-216	252-324	336-432	420-540
	Interface to inverter		RS485			
	Height	mm	788	1009	1230	1451
	Width/depth	mm	587/310			
	Weight	kg	99.5	135	170.5	206
	Ambient temperature	°C	-20...55			
	IP protection class		IP55			
	Certification / Safety Standard		UN38.3, VDE2510-50, IEC62619, IEC63056, IEC62477, IEC62040, CE, EMC, ROHS			

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

PLENTICORE G3 with LG RESU FLEX



LG Energy Solution		RESU FLEX 8.6	RESU FLEX 12.9	RESU FLEX 17.2
System data	Modul type	Li-Ion NMC, BMA 48.9kg ³⁾ , BPU 16.5kg ³⁾		
	Max. Charging/discharging current battery system	22/22		
	Max. Charging/discharging current battery input PLENTICORE S G3	17/17		
	Max. Power consumption with PLENTICORE S G3 - 4.0	3.3	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	3.3	5.0 ³⁾	5.5 ³⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	3.3	5.0 ³⁾	6.7 ³⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	30/30		
	Max. Power consumption with PLENTICORE M G3 - 8.5	4.3 ³⁾	6.5 ³⁾	8.5 ³⁾
	Max. Power consumption with PLENTICORE M G3 - 10	4.3 ³⁾	6.5 ³⁾	8.6 ³⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	4.3 ³⁾	6.5 ³⁾	8.6 ³⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	30/30		
	Max. Power consumption with PLENTICORE L G3 - 15	4.3 ³⁾	6.5 ³⁾	8.5 ³⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	4.3 ³⁾	6.5 ³⁾	8.5 ³⁾
	Max. Power consumption with PLENTICORE L G3 - 20	4.3 ³⁾	6.5 ³⁾	8.5 ³⁾
	Usable capacity 95% DoD ¹⁾	8.2	12.3	16.3
	Usable capacity 100% DoD ¹⁾	8.6	12.9	17.2
	Number of battery modules	2	3	4
	Nominal voltage	196	294	392
	Voltage range	192-265.6	288-398.4	384-531.2
	Interface to inverter	RS485		
	Height	665.2		
	Width/depth	665.2/445.2	665.2/593.6	665.2/742
	Weight	114.3	163.2	212.1
	Ambient temperature	-10...50		
	IP protection class	IP 55		
	Certification / Safety Standard	CE, RCM, UL1973, IEC62619, IEC62477-1, FCC, IEC61000-6-1, IEC61000-6-2, IEC61000-6-3		

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

3) The weight of the bracket and the design cover is not included

PLENTICORE G3 with PYLONTECH Force-H1




PYLONTECH Force			H1-V2 10.65 ³⁾	H1-V2 14.20 ³⁾	H1-V2 17.76 ³⁾	H1-V2 21.31 ³⁾	H1-V2 24.86 ³⁾
System data	Modul type		Li-Ion LFP 3.552 kWh, 48 V, 74 Ah, 36 kg				
	Max. Charging/discharging current battery system	A	40/40				
	Max. Charging/discharging current battery input PLENTICORE S G3	A	17/17				
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	2.4	3.3	4.0	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	2.4	3.3	4.1	4.9 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	2.4	3.3	4.1	4.9 ²⁾	5.7 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30				
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30				
	Max. Power consumption with PLENTICORE L G3 - 15	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	4.3 ²⁾	5.8 ²⁾	7.2 ²⁾	8.6 ²⁾	10.1 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	10.1	13.5	16.9	20.2	23.6
	Usable capacity 100% DoD ¹⁾	kWh	10.7	14.2	17.8	21.3	24.9
	Number of battery modules		3	4	5	6	7
	Nominal voltage	V	144	192	240	288	336
	Voltage range	V	130.5-162	174-216	217.5-270	261-324	304.5-378
	Interface to inverter		RS485				
	Height	mm	700	870	1040	1210	1380
	Width/depth	mm	600/380				
	Weight	kg	122	158	194	230	266
	Ambient temperature	°C	0...50				
	IP protection class		IP 55				
	Certification / Safety Standard		VDE2510-50, IEC62619, IEC62477, IEC62040, UN38.3, CE, EN 61000-6-2, EN 61000-6-3				

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

3) Pylontech Force-H1-V2 battery compatible with BMS modul: FC0500-40S-V2 mit article number 11FC0500ZZA-00013

PLENTICORE G3 with PYLONTECH Force-H2



PYLONTECH Force		H2-V2 7.10 ³⁾	H2-V2 10.65 ³⁾	H2-V2 14.21 ³⁾	H2-V2 17.75 ³⁾
System data	Modul type	Li-Ion LFP 3.552kWh, 96V, 37Ah, 35kg			
	Max. Charging/discharging current battery system	A			
	Max. Charging/discharging current battery input PLENTICORE S G3	A			
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	3.3	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	3.3 ²⁾	4.9 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	3.3 ²⁾	4.9 ²⁾	6.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30		
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	5.8 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	5.8 ²⁾	8.6 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	5.8 ²⁾	8.6 ²⁾	10.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30		
	Max. Power consumption with PLENTICORE L G3 - 15	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	5.8 ²⁾	8.6 ²⁾	11.5 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	6.7	10.1	13.5
	Usable capacity 100% DoD ¹⁾	kWh	7.1	10.7	14.2
	Number of battery modules		2	3	4
	Nominal voltage	V	192	288	384
	Voltage range	V	174-216	261-324	348-432
	Interface to inverter		RS485		
	Height	mm	822	1118	1414
	Width/depth	mm	450/296		
	Weight	kg	82	117	152
	Ambient temperature	°C	0...50		
	IP protection class		IP 55		
	Certification / Safety Standard		VDE2510-50, IEC62619, IEC62477, IEC62040, UN38.3, CE, EN 61000-6-2, EN 61000-6-3		

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

3) Pylontech Force-H2-V2 battery compatible with BMS modul: FC0500M-40S-V2 mit article number 11FC0500MZA-00013

PLENTICORE G3 with PYLONTECH Force-H3



PYLONTECH Force		H3 10.2	H3 15.36	H3 20.48	H3 25.6
System data	Modul type	Li-Ion LFP 5.12 kWh, 102,4 V, 50 Ah, 39 kg			
	Max. Charging/discharging current battery system	A			
	Max. Charging/discharging current battery input PLENTICORE S G3	A			
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	3.5	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	3.5	5.2 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	3.5	5.2 ²⁾	7.0 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30		
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	6.1 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	6.1 ²⁾	9.2 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	6.1 ²⁾	9.2 ²⁾	10.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30		
	Max. Power consumption with PLENTICORE L G3 - 15	kW	6.1 ²⁾	9.2 ²⁾	12.3 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	6.1 ²⁾	9.2 ²⁾	12.3 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	6.1 ²⁾	9.2 ²⁾	12.3 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	9.7	14.6	19.5
	Usable capacity 100% DoD ¹⁾	kWh	10.2	15.4	20.5
	Number of battery modules		2	3	4
	Nominal voltage	V	204.8	307.2	409.6
	Voltage range	V	185.6-230.4	278.4-345.6	371.2-460.8
	Interface to inverter		RS485		
	Height	mm	530	700	870
	Width/depth	mm	540/350		
	Weight	kg	92	131	170
	Ambient temperature	°C	0...50		
	IP protection class		IP 55		
	Certification / Safety Standard		UL1973, EC62619, IEC63056, VDE-AR-E 2510-50, UL9540A, UN38.3, CE RED, CE LVD, EN 61000-6-2, EN 61000-6-3		

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

PLENTICORE G3 with VARTA.wall



VARTA.wall		10	15	20
System data	Modul type	Rundzelle (21700) / Lithium-Ionen (NCA) 5.00 kWh, 100.8 V, 65 Ah, 37 kg		
	Max. Charging/discharging current battery system	A		
	Max. Charging/discharging current battery input PLENTICORE S G3	A		
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	3.4	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	3.4	5.1 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	3.4	5.1 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30	
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	5.2 ²⁾	7.9 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	5.2 ²⁾	7.9 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	5.2 ²⁾	7.9 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30	
	Max. Power consumption with PLENTICORE L G3 - 15	kW	5.2 ²⁾	7.9 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	5.2 ²⁾	7.9 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	5.2 ²⁾	7.9 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	9,5	14,25
	Usable capacity 100% DoD ¹⁾	kWh	10	15
	Number of battery modules		2	3
	Nominal voltage	V	201.6	302.4
	Voltage range	V	168 - 226.8	252 - 340.2
	Interface to inverter		RS485	
	Height	mm	1306	1752
	Width/depth	mm	605 / 135	
	Weight	kg	88	124
	Ambient temperature	°C	-2...42	
	IP protection class		IP 55	
	Certification / Safety Standard		CE, UN 38.3, IEC 62619:2017, VDE-AR-E 2510-50:2017-05, IEC 61000-6-2, IEC 61000-6-3	

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

PLENTICORE G3 with ZYC SIMPO HV



ZYC SIMPO HV		6.4	9.6	12.8	16	19.2	22.4	25.6	28.8 ³⁾
System data	Modul type	Li-Ion LFP 3.2 kWh, 64 V, 50 Ah, 36.4 kg							
	Max. Charging/discharging current battery system	A							
	Max. Charging/discharging current battery input PLENTICORE S G3	17/17							
	Max. Power consumption with PLENTICORE S G3 - 4.0	kW	2.2	3.3	4.0	4.0	4.0	4.0	4.0
	Max. Power consumption with PLENTICORE S G3 - 5.5	kW	2.2	3.3	4.4 ²⁾	5.4 ²⁾	5.5 ²⁾	5.5 ²⁾	5.5 ²⁾
	Max. Power consumption with PLENTICORE S G3 - 7.0	kW	2.2	3.3	4.4 ²⁾	5.4 ²⁾	6.5 ²⁾	7.0 ²⁾	7.0 ²⁾
	Max. Charging/discharging current battery input PLENTICORE M G3	A	30/30						
	Max. Power consumption with PLENTICORE M G3 - 8.5	kW	3.8	5.8 ²⁾	7.7 ²⁾	8.5 ²⁾	8.5 ²⁾	8.5 ²⁾	8.5 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 10	kW	3.8	5.8 ²⁾	7.7 ²⁾	9.6 ²⁾	10.0 ²⁾	10.0 ²⁾	10.0 ²⁾
	Max. Power consumption with PLENTICORE M G3 - 12.5	kW	3.8	5.8 ²⁾	7.7 ²⁾	9.6 ²⁾	10.5 ²⁾	10.5 ²⁾	10.5 ²⁾
	Max. Charging/discharging current battery input PLENTICORE L G3	A	30/30						
	Max. Power consumption with PLENTICORE L G3 - 15	kW	3.8	5.8 ²⁾	7.7 ²⁾	9.6 ²⁾	11.5 ²⁾	13.4 ²⁾	15,0 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 17.5	kW	3.8	5.8 ²⁾	7.7 ²⁾	9.6 ²⁾	11.5 ²⁾	13.4 ²⁾	15,4 ²⁾
	Max. Power consumption with PLENTICORE L G3 - 20	kW	3.8	5.8 ²⁾	7.7 ²⁾	9.6 ²⁾	11.5 ²⁾	13.4 ²⁾	15,4 ²⁾
	Usable capacity 95% DoD ¹⁾	kWh	6.1	9.1	12.2	15.2	18.2	21.3	27,4
	Usable capacity 100% DoD ¹⁾	kWh	6.4	9.6	12.8	16.0	19.2	22.4	28,8
	Number of battery modules		2	3	4	5	6	7	8
	Nominal voltage	V	128	192	256	320	384	448	512
	Voltage range	V	120-146	180-219	240-292	300-365	360-438	420-511	480-584
	Interface to inverter		RS485						
	Height	mm	670	860	1050	1240	1430	1620	1810
	Width/depth	mm	610/240						
	Weight	kg	92.5	128.9	165.3	201.7	238.1	274.5	310.9
	Ambient temperature	°C	-10...50						
	IP protection class		IP 65						
	Certification / Safety Standard		CEC, CE, UN 38.3, IEC 62619, VDE-AR-E 2510-50, IEC 61000-6-2, IEC 61000-6-3						

1) According to the battery manufacturer

2) Due to §14a (controllable consumers), please note that in Germany certain inverter/battery combinations must be externally controllable by the energy supplier so that the maximum possible battery charging capacity from the grid does not exceed 4.2 kWh. Further information on this can be found in the inverter operating instructions under 'External battery control via digital inputs'

3) From SW version 3.04.03.xxxxx

